

**Cobham SATCOM**

Lundtoftegaardsvej 93 D  
2800 Kgs. Lyngby  
Denmark

T: +45 39 55 88 00

F: +45 39 55 88 88

Date: November 2022

Document Number: 95-182648-A

## **IP Handset TT-3672A** **Software release version 1.20**

**Subject:**

Please be informed that a new software version 1.20 for the TT-3672A IP Handset has been released.

**Priority:**

- **MEDIUM:** It is recommended to apply this change / initiative to all units in stock. For units sold it is recommended to apply this change / initiative next time the system(s) is inspected.

**Changes in version 1.20:**

- **Updated features:**
  - Support for new version of display. Specifications unchanged.
- **Bug fixes:**
  - Handset did not report SIP Expire value during SIP registration.
    - In solutions using an external POE switch this could cause failure in detecting the IP Handset for up to 1 hour after a terminal restart.

**Action:**


**Note:** If present version in the IP Handset is ver. 1.10 or earlier, you will need to step-upgrade to ver. 1.11 before upgrading to latest version.

Download & extract file **IP Handset ver\_120.zip** located at Cobham SATCOM Sync partner login: <https://sync.cobham.com/> - or at the Cobham SATCOM Sync Support section <https://sync.cobham.com/satcom/support>.

1. Connected to the terminal, open the web Interface of the IP Handset.  
The IP address can be found in the Handset menu **Status** → **Network information**.
2. Select **UPLOAD FIRMWARE**.



3. Select **Browse...** then locate and select the software file **TT3672b\_1\_20\_1948.bin** extracted to your hard drive.




4. Choose **Upload Firmware** and verify that the upload is in progress.

- Installation of the software will take place when the file has been uploaded to the IP Handset.



The IP Handset display will also show the progress of the installation.

Ex.:



- When the installation is done, the IP Handset will restart and show the new version **1.20, build 1948**.



<b>HOME</b>	<b>HOME</b>
<b>CONTACTS</b>	Local time: 2022-11-15 16:00:47
<b>CALL LOG</b>	<b>HANDSET</b>
<b>SIP SETTINGS</b>	Name: TT-3672A IP Handset
<b>UPLOAD FIRMWARE</b>	Type: Wired
<b>IMPORT/EXPORT</b>	Serial number: 11744190
<b>HELP</b>	Software version: 1.20, build 1948
	Build date: 11/3/2022
	<b>NETWORK</b>
	DHCP server: Enabled (192.168.0.1)
	IP address: 192.168.0.16
	Subnet mask: 255.255.255.0
	Default gateway: 192.168.0.1
	MAC address: 00:11:CF:03:5E:A3
	<b>SIP</b>
	SIP profile: BGAN
	SIP status: Registered

7. End of updating procedure.

**Cobham SATCOM**  
Customer Service